

PSI 10

Single phase, electronic current source



Application:

The PSI 10 is a single-phase computer controlled current source, designed for use in meter test systems and in the laboratory. It is offered in three performance steps with 1000 VA, 2000 VA and 4000 VA output power available. The models are housed in a 19 inch plug-in unit, 6 height modules, independent of output power.

The PSI 10 generates an isolated, variable alternating current decoupled by a transformer. The output current is stabilized by an internal feedback loop and overlaid digital control loop for amplitude, phase angle and distortion factor. Harmonics can be added to the fundamental wave.

Internal circuits protect the source against overload, open outputs, mains breaks and energy recovery. The use of a voltage stabiliser at the entry point is not necessary.

Control of the source is achieved via an optical serial interface. A ring bus system and a synchronizing signal interface, both with optical terminals, allow the connection of several sources to a poly-phase system.

For safety reasons adding the STE 10 control unit to the PSU 10 is strongly recommended. The STE 10 has the following functions:

- On-off switch
- Emergency stop switch
- Protection against short circuits between U and I in the output circuits

Key features of the PSI 10

- Compact electronic current source (single phase)
- Controlled by PC via optical interface RS 232 C
- High accuracy and stability of the adjusted load independent of supply voltage deviations.
- Power efficiency > 85 %
- Current range: 1 mA to 120 A
- Output power: 1000 VA, 2000 VA, 4000 VA
- Generation of harmonics

Options

- CALegration software

Technical Data PSI 10

| Model | Description | 1000 VA | 2000 VA | 4000 VA |
|-----------------------------|------------------------|--|-------------------|------------------|
| Fundamental Data | | | | |
| Supply voltage | | | 3x230/400 V ±15 % | |
| | | | 50 / 60 Hz ± 5% | |
| Power consumption | maximum | 1200 W (1700 VA) | 2300 W (3400 VA) | 4600 W (6800 VA) |
| Weight | | 15 kg | 25 kg | 35 kg |
| Housing | 19"-plug-in unit | | 6 HE | |
| Dimension [mm] | Width x Height x Depth | | 483 x 265 x 600 | |
| Ambient temperature | | | +10 °C ... +40 °C | |
| Functional temperature | | | -10 °C ... +50 °C | |
| Storage temperature | | | -40 °C ... +80 °C | |
| Efficiency | At full load | | > 85 % | |
| Fundamental frequency range | | 45 ... 65 Hz (Optional mains voltage synchronization) | | |
| Resolution | | | 0.01 Hz | |
| Phase angle | | | 0 ... 360 degrees | |
| Kind of feedback control | | Digital feedback control with DFT - algorithm under laid feedback loop | | |

| Model | Description | 1000 VA | 2000 VA | 4000 VA |
|-------------------------|--------------------------|---------|-------------------|---------|
| Fundamental wave | | | | |
| Current range | | | 1 mA ... 120 A | |
| Internal ranges | 80 A ... 120 A | 1000 VA | 2000 VA | 4000 VA |
| | 12 A ... 80 A | 1000 VA | 2000 VA | 3200 VA |
| | 1.2 A ... 12 A | 480 VA | 480 VA | 480 VA |
| | 120 mA ... 1.2 A | 48 VA | 48 VA | 48 VA |
| | 12 mA ... 120 mA | 4.8 VA | 4.8 VA | 4.8 VA |
| | 1 mA ... 12 mA | 0.48 VA | 0.48 VA | 0.48 VA |
| Resolution | At the final range value | | 0.01 % | |
| Adjustment error | At the final range value | | < 0.05 % | |
| Distortion factor | On linear load | | < 0.5 % | |
| Spread | (Time base 5 s) | | < 0.05 % / 2 min. | |
| Drift | (Time base 150 s) | | < 0.005 % / h | |
| Load reaction | 0 % - 100 % load | | < 0.01 % | |
| Power factor of load | | | 1 ... 0.1 lag | |

| Model | Description | 1000 VA | 2000 VA | 4000 VA |
|---|----------------------|---------|-----------|---------|
| Additional signals | | | | |
| Generation of harmonics | 2. – 5. Harmonics | | Max. 40 % | |
| | 6. – 21. Harmonics | | Max. 10 % | |
| | Sum of all harmonics | | Max. 40 % | |
| Peak current on the individual current ranges and the belonging peak voltages | 187 A | 12.9 V | 25.9 V | 51.7 V |
| | 124 A | 19.5 V | 39 V | 62 V |
| | 18.7 A | 62 V | 62 V | 62 V |
| | 1.87 A | 62 V | 62 V | 62 V |
| | 187 mA | 62 V | 62 V | 62 V |
| | 18.7 mA | 62 V | 62 V | 62 V |